





The Unitronics PLC provided the perfect solution for our need for control. Whether it was safety, mechanical or functionality, the Jazz had it all.



Peter Spano,  
President of GTS



		<b>JZ20</b>						<b>JZ10</b>			
Article Number	Classic Panel	JZ20-R10	JZ20-R16	JZ20-R31	JZ20-T10	JZ20-T18	JZ20-T40	JZ10-11-UN20	JZ10-11-UA24	JZ10-11-PT15	
	Flat Panel	JZ20-J-R10	JZ20-J-R16	JZ20-J-R31	JZ20-J-T10	JZ20-J-T18	JZ20-J-T40	JZ10-J-UN20	JZ10-J-UA24	JZ10-J-PT15	
		6 Digital Inputs 4 Relay Outputs	6 Digital, 2 D/A, 2 Analog Inputs <sup>1</sup> 6 Relay Outputs	16 Digital, 2 D/A, 2 Analog Inputs <sup>1</sup> 11 Relay Outputs	6 Digital Inputs 4 Transistor Outputs	6 Digital, 2 D/A 2 Analog Inputs <sup>1</sup> 8 Transistor Outputs	16 Digital 2 D/A, 2 Analog Inputs <sup>1</sup> 20 Transistor Outputs	9 Digital, 2 D/A 1 Analog 1 PT100/TC Inputs <sup>1</sup> 5 Relay 2 Transistor Outputs	9 Digital, 2 D/A 2 Analog, 2 PT100/TC Inputs <sup>1</sup> 5 Relay, 2 Analog 2 Transistor Outputs	3 Digital, 3 D/A 3 PT1000/NI1000 Inputs <sup>1</sup> 5 Relay 1 Transistor Outputs	
<b>Inputs</b>											
Digital pnp/npn		6	8	18	6	8	18	11	11	6	
High-Speed Counters <sup>4</sup>		2 10kHz, 16-bit						1 5kHz, 16-bit			
Analog		None	2 10 or 12-bit, 0-10V & 2 10-bit 0-20mA, 4-20mA	2 10 or 12-bit, 0-10V & 2 10-bit 0-20mA, 4-20mA	None	2 10-bit, 0-10V & 2 10-bit 0-20mA, 4-20mA	2 10-bit, 0-10V & 2 10-bit 0-20mA, 4-20mA	2 10-bit, 0-10V & 1 10-bit 0-20mA, 4-20mA	2 10-bit, 0-10V & 2 10-bit 0-20mA, 4-20mA	3 10-bit 0-10V <sup>2</sup>	
Temperature Measurement		None	None	None	None	None	None	1 PT100/TC	2 PT100/TC	3 PT1000/NI1000	
<b>Outputs</b>											
Digital		4 relay	6 relay	11 relay	4 pnp	8 pnp	20 pnp	5 relay, 2 pnp	5 relay, 2 pnp	5 relay 1 pnp/npn	
High-Speed Outputs/PWM		None	None	None	2 PWM	2 PWM	2 PWM	2 PWM	2 PWM	1 HSO	
Analog		None	None	None	None	None	None	None	2 12-bit +/- 10V, 4-20mA	None	
<b>Program</b>											
Ladder Code Memory		48K						24K			
Memory Operands		256 coils, 256 registers, 64 timers									
<b>Operator Panel</b>											
Type		STN LCD									
Display Size		2 lines x 16 characters									
Keys		16 keys, 10 of which may be user-labeled									
<b>General</b>											
Power Supply		24VDC									
Battery		10 years typical at 25°C, battery back-up for RTC and system data, including variable data									
Clock		Real-time clock functions (date and time)									
Environment		NEMA4X/IP65 (when panel mounted)									
Standard		CE, UL									
Programming Port		Many of our products are also UL Class 1 Div 2 and GOST certified - please contact Unitronics						On Board Mini USB			Article No.: JZ-PRG sold separately
<b>Communication</b>											
Serial		RS232/RS485 Add-on port (isolated) Article No.: JZ-RS4 sold separately									
Ethernet		Ethernet add-on port Article No.: MJ20-ET1 sold separately						Not supported			

<sup>1</sup> These models comprise a total of 10/20 inputs (model-dependent), 6/16 (model-dependent) of these may be wired, in a group, as either digital npn or pnp. 2 inputs have added functionality. Both may be wired in a group as npn, pnp, or analog (voltage) inputs. Note that it is also possible to individually wire 1 input as a pnp input, and the other as an analog input. The two remaining inputs are analog (current).

<sup>2</sup> In order to download applications and enable communications, install Jazz<sup>®</sup> with the appropriate Add-on Module.

<sup>3</sup> Certain inputs can function as high-speed counters, or as normal digital inputs.

## Add-on modules and accessories<sup>2</sup>

**New!**

COM Port kit	Ethernet Communication Port	Program Cloner module	Keypad Slide kit
RS232/RS485 Add-on port (isolated) Article No.: JZ-RS4	Ethernet add-on port <b>Supported by Jazz<sup>®</sup> 2 series only</b> Article No.: MJ20-ET1*	Copy applications from PLC to PLC Article No.: MJ20-MEM1	Customize the Jazz <sup>®</sup> keypad to your application Article No.: MJ20-JZ-SL1

\* Not yet UL certified

# JAZZ OPLC™ Technical Specifications

Art. No. 130031 / Art. No. 131779

Art. No. 130030 / Art. No. 131780

## Models JZ20-R10/JZ20-J-R10 & JZ20-R16/JZ20-J-R16

This guide provides specifications for Unitronics' Micro-OPLC™ JZ20-R10/JZ20-J-R10 & JZ20-R16/JZ20-J-R16. You can find additional documentation on the Unitronics' Setup CD and in the Technical Library at [www.unitronics.com](http://www.unitronics.com).

## Technical Specifications

### Power supply

Input voltage	24VDC	
Permissible range	20.4-28.8VDC with less than 10% ripple	
Current Consumption	See Note 1	
	JZ20-R10/JZ20-J-R10	JZ20-R16/JZ20-J-R16
Max. current consumption	120mA@24VDC	136mA@24VDC
Typical power consumption	2.4W	2.6W

### Notes:

- To calculate the actual power consumption, subtract the current for each unused relay output and LCD backlight (if unused) from the maximum current consumption value.

	Per relay output	LCD backlight
Max. current per element	8.3mA@24VDC	35mA@24VDC

### Battery

Back-up	7 years typical at 25°C, battery back-up for RTC and system data, including variable data.
---------	--

### Digital Inputs

Number of inputs	JZ20-R10/JZ20-J-R10	JZ20-R16/JZ20-J-R16
	6 (one group) – see Note 2	8 (two groups) – see Notes 2 & 3
Input type	pnp (source) or npn (sink)	
Galvanic isolation	None	
Nominal input voltage	24VDC	
Input voltage		
pnp (source)	0-5VDC for Logic '0' 17-28.8VDC for Logic '1'	
nnp (sink)	17-28.8VDC for Logic '0' 0-5VDC for Logic '1'	
	I0-I5	I6-I7
Input current	3.7mA@24VDC	1.2mA@24VDC
Response time	10mSec typical	20mSec typical
Input cable length	Up to 100 meters, unshielded	
High speed inputs	Specifications below apply when wired as H.S.C. See Note 4.	
Resolution	16-bit	
Frequency	10kHz maximum	
Minimum pulse width	40µs	

## Notes:

- Both JZ20-R10/JZ20-J-R10 and JZ20-R16/JZ20-J-R16 comprise I0-I5; these inputs are arranged in a single group. Via wiring, the entire group may be set to either pnp or npn.
- Only JZ20-R16/JZ20-J-R16 comprises I6 & I7. These may be wired as either digital or analog inputs, as shown in the JZ20-R16/JZ20-J-R16 Micro PLC Installation guide. I6 & I7 may be wired as npn, pnp, or 0-10V analog inputs. 1 input may be wired as pnp, while the other is wired as analog. If 1 input is wired as npn, the other may **not** be wired as analog.
- I0 and I1 can each function as either a high-speed counter or as a normal digital input. When used as a normal digital input, normal input specifications apply.

---

## Digital Outputs

Number of outputs	JZ20-R10/JZ20-J-R10	JZ20-R16/JZ20-J-R16
	4 relay	6 relay
Output type	SPST-NO (Form A)	
Isolation	By relay	
Type of relay	Panasonic JQ1AP-24V or compatible	
Output current	5A maximum (resistive load)	
Rated voltage	250VAC / 24VDC	
Minimum load	1mA@5VDC	
Life expectancy	50k operations at maximum load	
Response time	10mS (typical)	
Contact protection	External precautions required (see Increasing Contact Life Span in the product's Installation Guide)	

---

## Analog Inputs

Number of inputs	JZ20-R16/JZ20-J-R16 only	
	4, according to wiring as described above in Note 3	
	AN0 and AN1	AN2 and AN3
Input range	0-20mA, 4-20mA	0-10VDC
Input impedance	154Ω	20KΩ
Maximum input rating	30mA	28.8V
Galvanic isolation	None	
Conversion method	Successive approximation	
Resolution	10 or 12-bit (0 to 4095) (Via Software)	
Conversion time	All analog inputs are updated every 8 PLC scans, regardless of how many inputs are actually configured.	
Precision	± 2%	
Status indication	Yes – if an analog input deviates above the permissible range, its value will be 4096.	
Input cable length	Up to 30 meters, shielded twisted pair	

---

## Display

Type	STN LCD
Illumination backlight	LED, yellow-green, software controlled (LCD backlight; enables the display to be viewed in the dark)
Display size	2 lines, 16 characters long
Character size	5x8 matrix, 2.95x5.55mm

## **Keyboard**

Number of keys	16 keys, including 10 user-labeled keys
Key type	Metal dome, sealed membrane switch
Slides	Slides may be installed in the operating panel faceplate to custom-label the keys and logo picture. An extra logo slide is included. A complete set of blank slides is available by separate order.

---

<b><u>Program</u></b>	See Note 5
Ladder code memory	48K (virtual)
Execution time	1.5 µSec for bit operations (typical)
Memory bits (coils)	256
Memory integers (registers), 16 bit	256
Timers	64
HMI displays	60 user-designed displays available
HMI variables	64 HMI variables are available to conditionally display text and data. List variables add up to 1.5K's worth of HMI capacity.

---

## **Communication**

GSM-support	Via a built-in USB port or - Add-On module. See Note 5-8 SMS messages to/from 6 phone GSM numbers, up to 1K of user-designed messages. Supports Remote Access.
MODBUS	Supports MODBUS protocol, Master-Slave
Baud rate	According to add-on port module
USB	
Port type	Mini-B
Galvanic isolation	No
Specification	USB 2.0 compliant; full speed
Baud rate range	300 to 115200 bps
Cable	USB 2.0 compliant; up to 3m

### **Notes:**

5. The JZ20 built-in USB port may be used for programming. Add-on Modules are available by separate order for communication and cloning. Note that the USB port and an Add-on module cannot be physically connected at the same time
6. Add-on module JZ-PRG, with 6-wires communication cable (supplied in PRG kit – see the JZ-PRG Installation Guide) can be used:
  - for programming
  - to connect a modem
7. Add-on module JZ-RS4 (RS232/485), with a standard 4-wire communication cable can be used:
  - for programming
  - to communicate with other devices (including modems/GSM)
  - for RS485 networking.
8. Add-on module MJ20-ET1 enables communication over 100 Mbit/s TCP/IP network:
  - Programming/data exchange with Unitronics software;
  - Data exchange via MODBUS TCP as Master or Slave.

## **Miscellaneous**

Clock (RTC) Real-time clock functions (date and time).

---

## **Environmental**

Operating temperature 0° to 50°C (32° to 122°F)  
Storage temperature -20° to 60° C (-4° to 140°F)  
Relative humidity (RH) 10% to 95% (non-condensing)  
Mounting method Panel mounted (IP65/NEMA4X)  
DIN-rail mounted (IP20/NEMA1)

---

## **Dimensions**

Size 147.5X117X46.6mm (5.807" X 4.606" X 1.835"). See Note 9  
Weight 300 g (10.6 oz)

## **Notes:**

9. For exact dimensions, refer to the product's Installation Guide.

---

## **Mounting**

Panel mounting Insert into cut-out: 117 x 89mm (WxH) 4.606"x 3.504"  
DIN-rail mounting Snap unit onto the DIN rail

The information in this document reflects products at the date of printing. Unitronics reserves the right, subject to all applicable laws, at any time, at its sole discretion, and without notice, to discontinue or change the features, designs, materials and other specifications of its products, and to either permanently or temporarily withdraw any of the forgoing from the market.

All information in this document is provided "as is" without warranty of any kind, either expressed or implied, including but not limited to any implied warranties of merchantability, fitness for a particular purpose, or non-infringement. Unitronics assumes no responsibility for errors or omissions in the information presented in this document. In no event shall Unitronics be liable for any special, incidental, indirect or consequential damages of any kind, or any damages whatsoever arising out of or in connection with the use or performance of this information.

The tradenames, trademarks, logos and service marks presented in this document, including their design, are the property of Unitronics (1989) (R"G) Ltd. or other third parties and you are not permitted to use them without the prior written consent of Unitronics or such third party as may own them.

DOC05002-B5 01/14